

REMARKS/ARGUMENTS

The specification has been conformed to correspond to the preferred format for U.S. patent applications as required in the Office Action, and a Substitute Specification and Comparison Copy are submitted herewith.

Claims 1-7 remain in this application.

Amendment is made to eliminate all multiple dependencies from the claims, thereby avoiding the need to pay the multiple dependent surcharge.

If the Examiner believes a telephone conference would expedite prosecution of this application, please telephone the undersigned at 415-576-0200.

Respectfully submitted,


J. George Jeka
Reg. No. 24,491

TOWNSEND and TOWNSEND and CREW LLP
Two Embarcadero Center, 8th Floor
San Francisco, California 94111-3834
Tel: (415) 576-0200
Fax: (415) 576-0300
JGS:jhw

60244291 v1



COMPARISON COPY

Deletions appear as Overstrike text
Additions appear as Double-Underlined text

SUBSTITUTE SPECIFICATION

Attorney Docket No. 15283A-26
Client No. STG 4/02

PATENT APPLICATION

~~MULTITURN~~MULTI-TURN ANGLE MEASURING DEVICETRANSDUCER

Inventor: Willibald Stobbe
Kirchbuehlstrasse 30
78166 Donaueschingen, Germany

Assignee: Sick AG
Sebastian-Kneipp-Strasse 1,
Waldkirch, D-79183, Germany

Entity: Large

TOWNSEND and TOWNSEND and CREW LLP
Two Embarcadero Center, Eighth Floor
San Francisco, California 94111-3834
Tel: 415-576-0200

MULTITURN ANGLE MEASURING DEVICEMULTI-TURN ANGLE TRANSDUCER

Background of the Invention

5 ~~Multiturn~~Multi-turn angle measuring devices are electromechanical sensors which detect absolutely several revolutions; i.e., within the resolution of the device the distinct angular position is always available even after the device has been switched on and completed several revolutions. Such angle measuring devices are used to measure shafts and axles and for positioning and control of electric motors in industry, especially in connection with manufacturing and handling machinery.

10 ~~Multiturn~~Multi-turn shaft encoders preferably have a compact construction and a high number of distinctly detectable turns. DE 28 17 172 C2 describes a shaft encoder which has a compact footprint in that the ~~multiturn~~multi-turn dimensional standards are driven by a spur reduction gear and lie within the circumferential region of the single code disk. In this case, 15 the sensors for detection of the ~~multiturn~~multi-turn and the single-turn rotational movements, or scales, are arranged on different circuit boards.

DE 34 29 648 C2 describes a ~~multiturn~~multi-turn shaft encoder which is used to scan an optical single code disk and another optical ~~multiturn~~multi-turn code disk which are arranged 20 within the circumferential region of the single code disk, which are arranged on one circuit board. Here as well, spur gears with axes of rotation parallel to that of the input shaft are used for the reduction.

A ~~multiturn~~multi-turn shaft encoder is also disclosed in DE 100 60 574 A1, which uses 25 detectors arranged on a circuit board for the detection of single and ~~multiturn~~multi-turn code carriers.

In the turn counter described in DE 100 01 676 C1, reed contacts arranged along a circumferential region of an input shaft are activated by means of a magnet rotating with the 30 input shaft and generating counting pulses. Such so-called counting ~~multiturn~~multi-turn shaft encoders, however, require a backup battery for counting when power is off. The reed contacts are subject to mechanical wear and therefore have only a limited lifetime. Moreover,

the battery takes up space and must therefore be positioned outside the sensor housing when the size of the ~~multiturn~~multi-turn shaft encoders must be kept small.

5 The reduction gearings of known mechanical ~~multiturn~~multi-turn shaft encoders are configured as spur gearings with gear turning axes that are parallel to the input shaft. When the input shaft has a large diameter, therefore, the driven gear of the first ~~multiturn~~multi-turn stage must have an even larger diameter than the one mounted on the input shaft in order to accomplish a reduction. However, this requires a much larger footprint. Otherwise the rotational speed of the first driven gear will be even higher than the rotational speed for the
10 gear fixed to the input shaft. Accordingly, a high rotational speed of the input shaft results in greater wear of the gears which leads to a reduced lifetime for the ~~multiturn~~multi-turn angle measuring device.

Summary of the Invention

15 It is an object of the present invention to develop a ~~multiturn~~multi-turn shaft encoder of compact construction and with relatively few ~~multiturn~~multi-turn stages, which is capable of measuring a high number of rotations at high rotational speed and/or large diameter of the input shaft.

This object is attained with the features of claim 1.

20 The ~~multiturn~~multi-turn angle measuring device of the invention has a first dimensional standard, which is non-rotatably connected to the input shaft, and which is sampled by a first scanning unit that determines the angular position of the input shaft. Additional dimensional standards measure the number of turns of the input shaft, each successive dimensional
25 standard being reduced by means of reduction gearing from the preceding dimensional standard, and they are arranged parallel to each other. There is one scanning device for each dimensional standard arranged on a circuit board. According to the invention, the driven or input gear connected to the input shaft and the transmission gear driven by the input gear have axes of rotation that are not parallel to each other, and the flanks of the teeth of the input
30 gear and of the driven gear do not run parallel to the axis of rotation of the particular gear. Furthermore, the number of teeth on the input gear is less than the number of teeth of the driven gear. The following transmission gears are again arranged parallel to the input shaft.

The drive gears and the driven gears of the first and second gear transmissions are spiral-tooth (worm) gears.

5 Thus, the driven gear of the first gear transmission stage is spirally geared to both the first input gear, joined to the input shaft, and to the driven gear of the second gear transmission stage. The drive gear of the first stage transmission can be slanted with respect to both the first drive gear and the remaining transmission gears, which in turn are arranged parallel to the input shaft. In this manner, sufficient gear reductions can be attained even for large input diameters, such as hollow shafts for example, while the footprint of the device remains small
10 because the first driven gear can be arranged at an angle, such as 90°. This avoids the above-mentioned disadvantages.

Benefits of the present invention are that even high rotational speeds can be measured, especially those of input shafts with large diameter, because of the high speed reduction at the
15 first transmission stage, which enables a very compact construction for the ~~multiturn~~multi-turn shaft encoder. Moreover, in such an arrangement the sensing units to detect the dimensional standards of the single and ~~multiturn~~multi-turn stages can be arranged on a single circuit board.

20 Advantageous embodiments of the invention are set forth in the dependent claims.

Advantageously, the drive gear connected to the input shaft and the drive wheel of the second gear transmission stage which drives the other transmission gears are also helical gears.

25 When the scanning unit of the first dimensional standard and the scanning units of the other dimensional standards are arranged on a single circuit board, considerable space can be saved and the shaft encoder is rendered more compact.

In a further aspect of the invention, the other dimensional standards are centrally carried by
30 gears having axes of rotation that are parallel to that of the input shaft, with additional intermediate gears arranged between them. The gears can be mounted on a single-piece ~~multiturn~~multi-turn unit.

In another embodiment of the invention, the other dimensional standards are diametrically magnetized permanent magnets.

Advantageously, the first dimensional standard is a transmissive Moiré code disk, which is illuminated by a transmitter, and which is detected by means of a photoelectric scanning unit.

As an alternative, the first dimensional standard can consist of one or more magnets, which are magnetized in sectors and detected by one or more magnetic sensors.

Brief Description of the Drawings

An example of the invention is shown in the following explained drawings. The drawings show:

Figure 1 is a schematic layout of a ~~multiturn~~multi-turn shaft encoder in cross section;

Figure 2 shows the ~~multiturn~~multi-turn transmission unit from different perspectives;

Figure 3 schematically shows the configuration of a gear; and

Figure 4 is an exploded, perspective view of the ~~multiturn~~multi-turn shaft encoder.

Description of the Preferred Embodiments

A ~~multiturn~~multi-turn angle measuring device 1 comprises a few modular components. It has a housing 3, an input shaft 2, a code disk 9 connected to the latter, a ~~multiturn~~multi-turn transmission unit 5 and a circuit board 6 on which are arranged the scanning units for detection of the code disk 9, as well as the ~~multiturn~~multi-turn dimensional standards 11, 12, 13.

In order to measure the absolute angular position of the input shaft 2 over one turn, the code disk 9 is illuminated by a phototransmitter 7 and detected by a scanning unit 10. The phototransmitter preferably is a light-emitting diode (LED).

The optical code disk 9 carries an absolute binary code, preferably a gray code or a sequential code, which can be formed by light/dark windows. For transmissive sampling, the encoding can be in the form of a thin, photolithographically structured chromium layer on a glass substrate. In addition, an incremental code track can be arranged on the code disk 9,

consisting of the highest possible number of division periods for a high angular resolution of the ~~multiturn~~multi-turn angle measuring device 1.

The input shaft 2 is mounted rotationally with respect to the shaft encoder housing 3, is preferably carried by ball bearings 4, and has an input drive gear 40 for reducing the speed of the first driven gear 41 of ~~multiturn~~multi-turn transmission unit 5. Input gear 40 necessarily has an axis of rotation parallel to that of input shaft 2. The first driven gear 41 of the ~~multiturn~~multi-turn stage 5, however, has an axis of rotation that is not parallel to the axis of rotation of input drive gear 40. Preferably, the first gear transmission stage, consisting of the input drive gear 40 connected to the input shaft 2 and the first driven gear of the ~~multiturn~~multi-turn stage 5, is a helical transmission with axes of rotation arranged at 90° from each other.

If the number of teeth of input drive gear 40 is ~~larger~~ smaller than the number of teeth of the first driven transmission gear 41, the speed of the input gear 40 will be reduced.

The input gear 40 connected to the input shaft 2 and the first driven gear 41 have axes of rotation D_{40} and D_{41} that are not parallel to each other. The flanks of the teeth Z_{40} of the drive gear 40 and the flanks of the teeth Z_{41} of the driven wheel 411 of gear 41 are not parallel to the axes of rotation, D_{40} or D_{41} , of gears 40 and 41. The number of teeth Z_{40} of the input gear 40 is smaller than the number of teeth Z_{41} of wheel 411 of the first driven gear 41, and the following transmission gears are again arranged parallel to input shaft 2. Pinion 412 of first driven gear 41 and the input wheel of the second transmission gear 31 are configured as helical gears.

Thus, the first driven gear 41 is helically toothed to both input gear 40, connected to the input shaft 2, and the second transmission gear 31. Thus, the first driven gear 41 can be oriented skewed to input gear 40 and skewed to the other transmission gears, which are in turn oriented parallel to the input shaft 2.

The ~~multiturn~~multi-turn transmission unit is represented in Fig. 2 from two different views. The first input gear 41 of transmission unit 5 drives further reduced gears 31, 34, 32, 35, 33. Gears 31, 32, 33 carry the position codes 11, 12, 13 for measuring the number of turns of input shaft 2. The speed of each code gear 31, 32, 33 is stepped down by an intermediate gear

34, 35 from the respective preceding code gear 31, 32, 33. Apart from input gear 40 and the last gear 33 of the transmission unit 5, each gear has one part designated as wheel and one part designated as pinion positioned adjacent to each other in the direction of the axis of rotation. The two parts of the gears have a different toothing. The part of the gear designated as the wheel serves to pick up the rotary motion from the pinion of the preceding gear.

Scanning units 21, 22, 23 (units 21 and 22 are not represented in the drawing) detect the position codes 11, 12, 13. Gears 31, 32, 33, which carry the code magnets 11, 12, 13, are preferably cylindrical gears with axes of rotation parallel to each other and preferably parallel to the axis of rotation of input shaft 2. The dimensional standards 11, 12, 13 are arranged as alternatingly magnetized sectors along their circumferences and are preferably diametric permanent magnets. Magnets 11, 12, 13 preferably have identical cylindrical geometries and identical magnetic field strengths and lie in a common plane. Scanning units 21, 22, 23 preferably lie likewise in a common plane and each one is located opposite the magnetic dimensional standard 11, 12, 13 being detected.

The scanning units 10 for the detection of code disk 9 connected to input shaft 2 and scanners 21, 22, 23 for the detection of the magnetic dimensional standards 11, 12, 13 are semiconductors which are arranged on the side of circuit board 6 facing code disk 9.

In the ~~multiturn~~multi-turn transmission unit 5 depicted in Fig. 2, the axis of rotation of the first driven gear 41 is perpendicular to the axis of rotation of drive gear 40 connected to input shaft 2. To provide gears 31, 32, 33, which carry the position magnets 11, 12, 13, with axes of rotation that are parallel to input shaft 2, the axis of rotation of gears 41 and 31 is again rotated 90° by means of another helical gear train consisting of the pinion of gear 41 and the wheel of gear 31. All other gears 34, 32, 35, 33 are cylindrical gears with axes of rotation that are parallel to the axis of rotation of the input shaft 2.

In the ~~multiturn~~multi-turn shaft encoder depicted in Figs. 1 and 4, all ~~multiturn~~multi-turn gears 31, 32, 33, 34, 35, 40, 41, including the dimensional standards 11, 12, 13, of the ~~multiturn~~multi-turn unit 5 are arranged entirely outside the circumference of dimensional standard 9 for the single stage.

Moreover, the dimensional standards 9, 11, 12, 13 for the single and ~~multiturn~~multi-turn stages are on the same side of circuit board 6. Thus, the scanning units 10, 21, 22, 23 for detection of dimensional standards 9, 11, 12, 13 can all be arranged on the side of the circuit board 6 facing the dimensional standards. This is especially advantageous when the scanning units are connected to circuit board 6 in like manners, such as a Chip-on-Board (CoB), by wire bonding. Additional electronic components can be arranged on the circuit board 6 as SMD (surface mounted device).

Furthermore, other compact configurations are possible. For example, the transmission gear stages for the ~~multiturn~~multi-turn unit can be partly or entirely within the circumference of code disk 9 of the single stage. The scanning units 10, 21, 22, 23 for the detection of the dimensional standard 9 of the single stage and the dimensional standards 11, 12, 13 of the ~~multiturn~~multi-turn transmission stages can optionally be mounted on a single circuit board 6.

In a further alternative embodiment, the circuit board 6 can be positioned between the first dimensional standard 9 for detecting the angular position of input shaft 2 and the ~~multiturn~~multi-turn unit 5. In this case as well, the scanning units for detecting the dimensional standards 9, 11, 12, 13 can be arranged on one circuit board 6.

In the sample embodiment represented in Figs. 1 and 4, the first dimensional standard 9 is constructed by a transmissive code disk. However, it is also possible to use a reflective code disk according to the invention. In such a case, light transmitter 7 is positioned on the same side as the scanning unit 10. Preferably, the light transmitter 7 and the scanning unit 10 are arranged on a common circuit board 6.

For the detection of an optical code disk 9, the scanning unit 10 consists of photosensitive semiconducting layers structured according to the coding on the dimensional standard 9, which generate one or more analog or digital electrical position signals.

The scanning units 21, 22, 23 for the detection of the magnetic ~~multiturn~~multi-turn dimensional standards 11, 12, 13 preferably consist of several magnetic sensors that are integrated on a semiconductor substrate, such as Hall or magnetoresistive (MR) sensors. The resolution of the angular position of the position magnets 11, 12, 13 serving as the dimensional standards, which is produced by evaluation circuits each connected to the

scanning units 21, 22, 23, amounts to at least n bits, where 2^n is larger than the reduction factor between every two ~~multiturn~~multi-turn gears 31, 32, 33 carrying the position magnets 11, 12, 13.

List of reference numbers

	1	Source of rotation
	2	Input shaft
5	3	Housing
	4	Bearing
	5	Multiturn <u>Multi-turn</u> transmission unit
	6	Circuit board
	7	Transmitter
10	8	Collimator lens
	9	Code disk/dimensional standard
	10, 21, 22, 23	Scanning units
	11, 12, 13	Magnets/dimensional standards
	31, 32, 33	Code gears
15	34, 35	Intermediate gears
	40	Input drive gear
	41	Driven gear of the multiturn <u>multi-turn</u> unit 5
	411	Wheel of gear 41
	411	Pinion of gear 41
20	D ₄₀ , D ₄₁	Axes of rotation of gears 40, 41
	Z ₄₀ , Z ₄₁	Teeth of gear 40 and of wheel 411 of gear 41

60244362 v1